

Sheepylove Hot Teacher Build Doc

Updated: 2026-03-18

It's woolly, it's greasy, it's Sheepylove.

Disclaimer: All trademarks and registered trademarks are the property of their respective owners. The company, product, and service names used in this document are for comparative purposes only. Use of these names, logos, and brands does not imply affiliation nor endorsement.

Sounds like LPD Sixty8 with mods by Celestial Engineering

Add a boost control, change up the EQ, it's another fun improvement on a great pedal.





Copyright: Sheepylove.com 2026-03-18

Bill of Materials

Reference	Value	Quantity	Notes
C1	100u	1	
C2	47u	1	
C3	10n	1	
C4,C5	3n9	2	
C6	15n	1	
C7	750p	1	
C8	68n	1	
C9,C12,C16	1u	3	
C10	1n	1	
C11	100n	1	
C13	4n7	1	
C14	470p	1	
C15	5n6	1	
D1	1N5817	1	
D2	LED	1	
D3,D4	Ge	2	Any Ge diodes will work.
IC1,IC2	TL072	2	
POT1	A10k	1	
POT2,POT4,POT5	C50k	3	
POT3	C25k	1	
POT6	C100k	1	
Q1	2N5087	1	
Q2,Q3	2N7000	2	2N7002 for SMD
R1	CLR	1	
R2	10	1	
R3,R4	4k7	2	
R5	1M	1	
R6,R23,R27	1k	3	
R7	560k	1	
R8,R21	10k	2	
R9	470k	1	
R10-R12,R18	47k	4	
R13	6k8	1	
R14,R19	3k3	2	
R15	68k	1	
R16	2k7	1	
R17,R20	27k	2	
R22	270k	1	
R24	1k5	1	
R25	220k	1	
R26	39k	1	

Reference	Value	Quantity	Notes
SW1	0n/0n	1	

Copyright: Sheepllove.com 2026-03-18



Sheet: /
File: HotTeacher.kicad_sch


Title:

Size: A4 Date:

KiCad E.D.A. 9.0.7

Rev:

Id: 1/1



Sheepylove Drill Template

-20.3 0 20.3

38.1 • • •

12.7 • • •

0 +

-12.7 • • LED



-45.1 • Footswitch

All units are in millimeters.